

DIGITAL INVERTOR GENERATOR


Max. output: 1,000

UM330142

- *Inverter Technology for Sensitive equipment*
- *1000W Maximum output power*
- *Safety cut out switch for greater safety*
- *Large fuel tank*



Rated output: 900 W
Max. output: 1,000 W
Power connection (12V d. c.): 70 W
Rated voltage: 230V / 12V d. c.
Rated current: 4A (230V)/6A (12V DC)
Frequency: 50Hz
Type: 1 cylinder, 4 stroke, air cooled, OHV.
Displacement: 52.6cc
Max. Power: 1.4kW / 1.9HP
Fuel: Normal lead-free gasoline
Tank capacity: 2.7L
Consumption at 2/3 load: approx. 0.65L/h
Protection type: IP 23M
Noise level: Lwa(7M):68 dB (A)



HIMOUNT INDUSTRIAL CO., LTD.
7TH FL. No.325, FU HSING N. ROAD.
TAIPEI, TAIWAN,
TEL: 886-2-27135577 FAX: 886-2-27152218
E - MAIL: himount@himount.com
[http:// www.himount.com](http://www.himount.com)